

**CitySource 96 (Single colour) - DMX protocol**

Version 1.0

Mode				Value	Function	Type of control
1	2	3	4			
-	-	1	1	0 - 255	<b><u>Dimmer –LED array 1</u></b> Dimmer intensity from 0% to 100%	proportional
-	-	2	2	0 - 255	<b><u>Dimmer –LED array 2</u></b> Dimmer intensity from 0% to 100%	proportional
-	1	-	3	0-31 32-63 64-95 96-127 128-143 144-159 160-191 192-223 224-255	<b><u>Strobe –both LED arrays</u></b> Shutter closed Shutter open Strobe-effect from slow to fast Shutter open Opening pulses in sequences slow--> fast Closing pulses in sequences fast --> slow Shutter open Random strobe-effects from slow to fast Shutter open	step step proportional step proportional proportional step proportional step
1	2	-	4	0 - 255	<b><u>Dimmer–both LED arrays</u></b> Dimmer intensity from 0% to 100%	proportional
-	3	-	5	0 - 255	<b><u>Dimmer fine–both LED arrays</u></b> Fine dimmer intensity from low to high	proportional