

ROBE lighting s .r. o., Hazovice 2090 75661 Roznov pod Radhostem Czech Republic Tel: +420-571-751500 Fax: +420-571-751515 Email: info@robe.cz

# **LEDBlinder 148 LT**

The LEDBlinder 148 LT is a 4-way version of the LEDBlinder 196 LT. The unit is fitted into the industry standard 4-lite casing and offers set and lighting designers all the options. It has 4 LED modules, each with 12 RGB LEDs. Each two pairs of modules are separately controllable.This product is aimed at all stage lighting markets and television productions and for arenas and larger venues.





## **Technical Specification**

#### Source

- High-Power 1W Luxeon LEDs
- 16 Red LEDs, 16 Green LEDs, 16 Blue LEDs
- < 50.000 hrs Rated Life

#### **Beam angle**

• 25° beam angle of each LED

#### Frost, diffusion

• Optional frost filters (glass or film) for even light distribution

#### Colours

- 16,7 million colours (24 bit)
- Pre-programmed colours & rainbow effect
- Dynamic colour balance between white and red, green, blue colours during production
- White balance pre-programmed via LED control panel

#### Dimmer, Strobe

- Electronic dimmer for light output adjustment from 0 to 100%
- High speed white or full colour strobe, flash rate 1-25 fps

#### **Mechanical specification**

- Height: 510 mm (20.0")
- Width: 480 mm (18.9")
- Depth: 190 mm (7.5")
- Weight: 12 kg (26.5 lbs)

#### **Thermal specification**

- Maximum ambient temperture: 40°C (104°F)
- Maximum housing temperature: 60°C (140°F)



ROBE lighting s .r. o., Hazovice 2090 75661 Roznov pod Radhostem Czech Republic

### **Control and programming**

- Protocol: USITT DMX-512
- Control options: DMX, Auto-trigger
- Operation modes: Master/Slave, Stand-alone
- Programs: 6 built-in programs + 3 user editable programs up to 30 steps each
- Display: 4 digit LED
- Manual control of all DMX channels via LED control panel
- 2 pairs of LED modules

#### **DMX channels**

- Mode 1: 9 channels
- Mode 2: 6 channels
- Mode 3: 6 channels
- Mode 4: 3 channels

#### Connection

- Control: DMX 512
- DMX connection: 3-pin or 5-pin XLR-sockets

#### **Power consumption**

- Input Voltage: 100-240 V, 50/60 Hz
- Fuse: T 2A
- Max. Power Consumption: 70 VA

#### **Optional accessories**

- Set glass frost
- Set film frost