

MediaSpinner 50 AT Multimedia- DMX Protocol-version 1.0

Channel	Value	Function	Type of control
1	0 - 255	Pan coarse Coarse control of pan movement by 450°	proportional
2	0 - 255	Pan Fine Fine control of pan movement	proportional
3	0	Pan speed Max. speed (tracking mode)	step
	1 - 255	<i>Pan speed-set Speed Mode in menu: Pan Mode</i> Speed from max. to min. (vector mode)	proportional
	1 - 255	<i>Pan time - set Time Mode in menu: Pan Mode</i> Time from 0,1 s to 25,5 s.	proportional
4	0 - 129	Special functions Standard operation (fixture is controlled by channels 1, 2 and 3)	step
	130 - 139	Reset of pan	step
	140 - 208	Reserved	
	210 - 219	Switching On power supply of load	step
	220 - 229	Reserved	
	230 - 239	Switching Off power supply of load	step
240 - 255	Reserved		